





Product Line Drawing




Input Parameters	
Input Voltage Range	220-240 Vac
Input Current	<0.03A
Power Factor	> 0.32
Frequency	50Hz
Ambient Temperature	40C
Ambient Temperature	0-40C
Class	II
Maximum Input Power (While Charging Battery)	2.6W
Average Input Power (Not Charging Battery)	2.3w


Input Voltage Range	220-240 Vac
Input Current	<0.03A
Power Factor	> 0.32
Frequency	50Hz
Ambient Temperature	40C
Ambient Temperature	0-40C
Class	II
Maximum Input Power (While Charging Battery)	2.6W
Average Input Power (Not Charging Battery)	2.3w

Product Instal	l Picture
----------------	-----------



Emergency Parameters	
Emergency Duration	180minutes
Battery Code(s)	zc-batt-1A1-ACA
Battery Type	LiFePO4
Input Battery Voltage	2.0-4.0 Vdc
Output Battery Voltage	2.0-3.65 Vdc
Input Battery Current	300mA
Output Battery Current	0.08A
Charging Time	24 hours
Emergency Output Power	1.0 W
Exit Sign View Distance	30m















Polycarbonate
RAL9011
Push Terminal (0.5-2.5mm2)
Surface mount/Jack chain mount/Wall mount
IP20
315mm
204mm
52mm

Standards	
IEC 60598-1	Yes
IEC 60598-2-22	Yes
IEC 62034	Yes



Wiring Diagram



Required Safety Warnings

- · This product must only be installed by a licensed electrician.
- \cdot Before commencing installation turn off and isolate the electrical supply
- \cdot Risk of accidental contact with live parts. Do not energise with product open or disassembled.
- · The only replaceable part is the battery
- \cdot Do not attempt to service other parts of the fitting as this will void the warranty.
- \cdot After installation allow the battery to charge for 24 hours before carrying out discharge testing.
- · WARNING: ALL MAINTENANCE, SUCH AS BATTERY CHANGE ON THIS LUMINAIRE, TO BE PERFORMED BY QUALIFIED PERSONNEL ONLY. DE-ENERGISE ALL SUPPLIES BEFORE MAINTENANCE.
- \cdot As the installer, it is your responsibility to ensure you comply to all relevant building and safety codes. for example the BCA, AS3000
- \cdot The replacement of the battery is needed when they no longer meet their rated duration of operation after the corresponding recharge period.
- $\cdot \, \text{For indoor use only} \,$
- \cdot Dongguan Evolt Electronics Co., Ltd. No.3 Qinghu East Road Yuliangwei Village, Qingxi TownDongguan City, Guangdong, China 523649









Photometrics







